

EDI X12 990 Response to a Load Tender (LTL)

Version: V4010&4030 Author: One Network Integration Last updated: Sep 2019

> One Network Enterprises 4055 Valley View Lane Dallas, TX 75244

Revision History

Revision	Date	Prepared By	Comments
1.0	9/10/2019	Integration Team	

Table of Contents

90	90 Response to a Load Tender	4
•		
	ISA Interchange Control Header	5
	GS Functional Group Header	7
	ST Transaction Set Header	8
	B1 Beginning Segment for Booking or Pick-up/Delivery	9
	N9 Reference Identification	9
	SE Transaction Set Trailer	10
	GE Functional Group Trailer	10
	IEA Interchange Control Trailer	10
	Sample FDI 990:	11

990 Response to a Load Tender

Functional Group=**GF**

Purpose: The purpose of this document is to provide information pertaining to the Standard EDI Integration that is offered by One Network Enterprises (ONE).

This Draft Standard contains the format and establishes the data contents of the Response to a Load Tender Transaction Set (990) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide general information relative to a specific shipment. The Response to a Load Tender (**Other than TRUCK Load**) is used as the response to a Motor Carrier Shipment Information Transaction Set (204) which has been used as a load tender. The EDI 990 message will be sent from the Carrier to One Network and will be used to accept or reject the tender for the load (movement).

EDI 990 Segments:

<u>Pos</u>	<u>Id</u>	Segment Name	Req	Max Use	<u>Repeat</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1		Must use
	GS	Functional Group Header	М	1		Must use
010	ST	Transaction Set Header	М	1		Used
020	B1	Beginning Segment for Booking or Pick-up/Delivery	M	1		Used
030	N9	Reference Identification	0	1		Recommended
070	SE	Transaction Set Trailer	М	1		Used
	GE	Functional Group Trailer	М	1		Must use
	IEA	Interchange Control Trailer	М	1		Must use

ISA Interchange Control Header

Mandatory

Max: 1

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Ref	Element Description	Req	Туре	Min/Max	Usage
ISA01	Authorization Information Qualifier	М	ID	2/2	Must use
	Description: Code to identify the type of information in	the Auth	orization	Information	All valid
	standard codes are used.				
ISA02	Authorization Information	М	AN	10/10	Must use
	Description: Information used for additional identificati				
	interchange sender or the data in the interchange; the Authorization Information Qualifier (I01)	type of in	formatio	n is set by th	e
ISA03	Security Information Qualifier	М	ID	2/2	Must use
	Description: Code to identify the type of information in All valid standard codes are used.	the Secui	rity Infor	mation	
ISA04	Security Information	М	AN	10/10	Must use
	Description: This is used for identifying the security info			_	9
	sender or the data in the interchange; the type of information Qualifier (103)	mation is	set by th	e Security	
ISA05	Interchange ID Qualifier	М	ID	2/2	Must use
	Description: Qualifier to designate the system/method	of code st	tructure	used to desig	gnate
	the sender or receiver ID element being qualified				
	All valid standard codes are used.				
ISA06	Interchange Sender ID	М	AN	15/15	Must use
	Description: Identification code published by the sende		•		9
	receiver ID to route data to them; the sender always co element	des this v	alue in t	he sender ID	
ISA07	Interchange ID Qualifier	М	ID	2/2	Must use
	Description: Qualifier to designate the system/method	of code st	tructure	used to desig	gnate
	the sender or receiver ID element being qualified				
	Code List Summary				
	Code Name				
	02 SCAC (Standard Carrier Alpha Code)				
ISA08	Interchange Receiver ID	М	AN	15/15	Must use
ISA08	Interchange Receiver ID Description: Identification code published by the receiv			15/15 nen sending,	Must use
ISA08		er of the	data; Wł	nen sending,	it is
ISA08	Description: Identification code published by the receiv	er of the	data; Wł	nen sending,	it is
ISA08	Description: Identification code published by the receivused by the sender as their sending ID, thus other particular	er of the	data; Wł	nen sending,	it is
	Description: Identification code published by the receivused by the sender as their sending ID, thus other partireceiving ID to route data to them	er of the es sendin	data; Wh g to ther	nen sending, n will use thi	it is s as a
	Description: Identification code published by the receivused by the sender as their sending ID, thus other partireceiving ID to route data to them Interchange Date	er of the es sendin	data; Wh g to ther	nen sending, n will use thi	it is s as a

ISA11	Interchange Control Standards Identifier	М	ID	1/1	Must use
	Description: Code to identify the agency responsible for to message that is enclosed by the interchange header and the All valid standard codes are used.		rol stand	dard used by	the
ISA12	Interchange Control Version Number	М	ID	5/5	Must use
	Description: Code specifying the version number of the in	nterchar	ige cont	rol segment	S
ISA13	Interchange Control Number	М	N0	9/9	Must use
	Description: A control number assigned by the interchang	ge sende	er		
ISA14	Acknowledgment Requested	М	ID	1/1	Must use
	Description: Code sent by the sender to request an intercal All valid standard codes are used.	change a	cknowle	edgment (TA	1)
ISA15	Usage Indicator	М	ID	1/1	Optional
	Description: Code to indicate whether data enclosed by the production or information All valid standard codes are used.	his inter	change	envelope is	test,
ISA16	Component Element Separator	М		1/1	Optional
	Description: Type is not applicable; the component elemedata element; this field provides the delimiter used to separate a composite data structure; this value must be different to segment terminator	parate c	ompone	ent data eler	nents within

GS Functional Group Header

Mandatory

Max: 1

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Semantics:

- 1. GS04 is the group date.
- 2. GS05 is the group time.
- 3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments: A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

Ref	Element Description	Req	Туре	Min/Max	Usage
GS01	Functional Identifier Code	М	ID	2/2	Must use
	Description: Code identifying a group of application related Code List Summary Code Name GF Response to a Load Tender (990)	ed trans	action se	ets	
GS02	Application Sender's Code	М	AN	2/15	Must use
	Description: Code identifying party sending transmission; partners	codes a	greed to	by trading	
GS03	Application Receiver's Code	М	AN	2/15	Must use
	Description: Code identifying party receiving transmission partners	n; codes	agreed [·]	to by trading	
GS04	Date	М	DT	8/8	Must use
	Description: Date expressed as CCYYMMDD				
GS05	Time	М	TM	4/8	Must use
	Description: Time expressed in 24-hour clock time as follows: HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = seconds (00-59) and DD = decimal seconds; decimal seconds (0-99) and DD = hundredths (00-99)	= minut	es (00-59	9), S = intege	r
GS06	Group Control Number	М	N0	1/9	Must use
	Description: Assigned number originated and maintained	by the	sender		
GS07	Responsible Agency Code	М	ID	1/2	Must use
	Description: Code identifying the issuer of the standard; t with Data Element 480 All valid standard codes are used.	his code	e is used	in conjunction	on
GS08	Version / Release / Industry Identifier Code	М	AN	1/12	Must use
	Description: Code indicating the version, release, subreless standard being used, including the GS and GE segments; in DE 480 positions 1-3 are the version number; positions level of the version; and positions 7-12 are the industry o (optionally assigned by user); if code in DE455 in GS segments	if code i 4-6 are r trade a	n DE455 the rele associati	in GS segme ase and subron identifier:	nt is X, then release,

Max: 1

ST Transaction Set Header Mandatory

User Option (Usage): Used

Purpose: To indicate the start of a transaction set and to assign a control number

Ref	Element D	escription		Req	Туре	Min/Max	Usage
ST01	Transactio	n Set Identifier Code		М	ID	3/3	Used
	Description Code List S	n: Code uniquely identifying a Tran iummary	saction Set				
	Code 990	Name Response to a Load Tender					
ST02	Transactio	n Set Control Number		М	AN	4/9	Used
		n: Identifying control number that group assigned by the originator fo		•	nin the t	ransaction se	t

B1 Beginning Segment for Booking or Pick-up/Delivery

Mandatory

Max: 1

User Option (Usage): Must Use

Purpose: To transmit identifying numbers, dates, and other basic data relating to the transaction set

Element Summary:

Ref	Element D	escription		Req	Type	Min/Max	Usage		
B101	Standard Carrier Alpha Code O ID 2/4 Used								
	•	n: Standard Carrier Alpha Code with Carrier SCAC Code							
B102	Shipment I	dentification Number		М	AN	1/30	Used		
		n: Identification number assigned t he shipment from origin to ultimat	•	-			•		
B104	Reservatio	n Action Code		0	ID	1/1	Used		
	Description: Code identifying action on reservation or offering								
	Code	Name							
	Α	Accept							
	D	Reject							

N9 Reference Identification

Optional

Max: 1

User Option (Usage): Recommended

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Ref	Element Descri	ption		Req	Туре	Min/Max	Usage	
N901	Reference Iden	tification Qualifier	М	ID	2/3	Used		
	Description: Co	de qualifying the Reference Iden	tification					
	Default to CN =	Default to CN = Pro Number						
	Code List Summ	Code List Summary						
	Code	Name						
	ZZ	Mutually Defined						
N902	Reference Iden	tification		Χ	AN	1/30	Used	
	Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier							
N903	Free-form Desc	ription		Х	AN	1/45	Used	
	Hub Company a	abbreviation	•	•				

SE Transaction Set Trailer

Mandatory

Max: 1

User Option (Usage): Used

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments

(including the

beginning (ST) and ending (SE) segments)

Element Summary:

Ref	Element Description	Req	Туре	Min/Max	Usage			
SE01	Number of Included Segments M N0 1/10 Used							
	Count of segments included (does not include Header and	d Footer	segmer	nts				
CEO2	Transaction Set Control Number	М	ΛNI	1/0	111			
SE02	Transaction Set Control Number M AN 4/9 Used Same as Transaction Set Control Number as in ST segment							

GE Functional Group Trailer

Mandatory

Max: 1

User Option (Usage): Must Use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

Ref	Element Description	Req	Туре	Min/Max	Usage		
GE01	Number of Transaction Sets Included M NO 1/6 Mu						
	Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	Group Control Number	М	N0	1/9	Must Use		
	Description: Assigned number originated and maintained The data interchange control number GE02 in this trailer element in the associated functional group header, GS06	must be		al to the sam	e data		

IEA Interchange Control Trailer

Mandatory

Max: 1

User Option (Usage): Must Use

Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Ref	Element Description	Req	Туре	Min/Max	Usage			
IEA01	Number of Included Functional Groups M NO 1/5 Must Use							
	Description: A count of the number of functional groups included in an interchange							
IEA02	Interchange Control Number	М	N0	9/9	Must Use			
	Description: A control number assigned by the interchang	ge sende	r					

Sample EDI 990:

IEA*1*001001956

ISA*00* *00* *ZZ*CARA *ZZ*ELOGEX *040819*1523*U*00403*001001956*0*P*>
GS*GF*CARA*ELOGEX*20180819*1523*001001960*X*004030
ST*990*001001966
B1*CARA*Movement001*20180820*D
N9*CN*12345*CUSTA
SE*4*001001966
GE*1*001001960